



**Notes -**

- Maximum distance from power supply to monitor using 6pr BT cable CW1308 is 50M.
- For distances 50M - 100M please add 2 x 1.0mm Brown and Blue singles per monitor (connections 1 & 3).
- Maximum distance from power supply to entry panel using 1.5mm singles is 20M.
- If using a DC release/maglock, a DC power supply and relay will be required.

- On switcher AN7775 remove the PM jumper and adjust timer trimmer to minimum.
- Set termination switch to 'L' position on monitor back plate.
- Fit MOV suppression across lock connections to protect against back EMF.

Title	2 door VR 1 button calling 2 handsfree monitors coded access to 1 panel		
Drawing No	BVG00051/VID/REV		
Date	28/01/2010		
Revision	02	Author	MD

**bitronvideo**

STYLE AND INNOVATION  
www.bitronvideo.co.uk

NOTE--TO MAKE THE SAME CODE OPERATE BOTH GATES TOGETHER PROGRAMME THE SAME CODE TWICE INTO TWO DIFFERENT MEMORY SLOTS BUT SELECTING A DIFFERENT RELAY FOR EACH.